

Behringer HA8000V2 Specs

Number of Channels	8
Input Connections	2 x 1/4" TRS Phone (L/Mono, R) Main Input 1, Balanced 2 x 1/4" TRS Phone (L/Mono, R) Main Input 2, Balanced 8 x 1/4" Stereo Phone Direct Ins
Input Impedances	Main: 20 kOhms balanced / 10 kOhms unbalanced Direct In: 15 kOhms
Line Max Input Level	+ 16 dBu
CMMR	> 50 dB
Headphone Outputs	8 x 1/4" TRS stereo on front panel 8 x 1/4" TRS stereo on back panel
Maximum Output Level	+24 dBm @ 100 Ohms +19 dBm @ 8 Ohms
Function Controls	1 x Main In 1 Level Control Knob 1 x Main In 2 Level Control Knob 8 x Channel Output Level Control Knobs 8 x Main In 1/Main In 2 Channel Monitoring Switches 8 x Mono Channel Monitoring Switches
Frequency Response	10 Hz - 150 kHz, +/-3 dB

THD + N	0.007% typ. @ +4 dBu, 1 kHz, Gain 1
Noise	22 Hz - 22 kHz >80 dB @ 0 dBu
Dynamic Range	103 dB (22 Hz to 22 kHz)
Display	Input Level: 5-digit LED: Output Level: 8-digit LED: -30, -24, -18, -12, -6, -3, 0 dB, CLIP
Specialties	Up to 150 kHz Frequency Response Individual Output Level Displays Individual Direct Inputs Per Channel
Power Supply	Autorange, 100-240 VAC, 50/60 Hz Fuse: T1.25AL 250 V
Power Consumption	35 W
Dimensions	1.75 x 19 x 5.9" (44.5 x 482.6 x 149 mm)
Weight	4.2 lb (1.9 kg)

Packaging Info

Package Weight	5 lb
Box Dimensions (LxWxH)	20.5 x 9.7 x 4.3"