

Soundcraft GB2R-16 Specs

Total # Of Inputs	16-Channels
Mic/Line Inputs	16 Mono Balanced XLR Microphone 16 Mono Balanced 1/4" TRS Phone Line
Stereo Line Inputs	No
In-Line Inputs>Returns	No
AUX Sends	6-Total 4 Balanced XLR 2 Balanced 1/4" TRS Phone
AUX Returns	2 Stereo L/R 1/4" TRS Phone
Inserts	1/4" TRS Phone All Mono Inputs, Mix Output and Subgroup Outputs
BUS (Group) Outputs	Stereo Output Only
2 Trk Master I/O	Mix Output - 2 Balanced XLR Mono Output - 1 Balanced XLR
ALT I/O	Direct Outputs (All Mono Channels) - 1/4" TRS Phone
Monitor Outputs	Stereo L/R 1/4" TRS Phone

EQ Section	Mono Input Channels: High pass Filter - 100Hz, 18dB/Octave HF - 13kHz, +/-15dB, 2nd order shelving Hi-Mid - 550Hz-13kHz, +/- 15dB, Q=1.5 Lo-Mid - 80Hz-1.9kHz, +/- 15dB, Q=1.5 LF - 80Hz, +/- 15dB, 2nd order shelving
Solo/Mute	Mute, Mix, Subgroup and PFL on all channels
Channel Level Control	100mm Fader
Trim/Gain Control	Rotary Controls
Phantom Power	+48V
Metering	Input Channels: Single LEDs, Signal Present & Peak Outputs: 2 tri-color, 12-segment LEDs
Frequency Response	20Hz to 20kHz < 1dB
Dynamic Range	<i>Not Specified By Manufacturer</i>
Signal-to-Noise Ratio	-128dBu, Measured RMS, 22Hz to 22kHz Bandwidth
Total Harmonic Distortion (THD)	<0.006%

Power Supply	Internal PSU: 90V-240V AC, 50/60Hz Universal Input Power Consumption: Less than 100W
--------------	--

Dimensions (WxHxD)	17.36 x 8.20 x 21.05" (441 x 208.42 x 534.79mm)
--------------------	---

Weight	<i>Not Specified By Manufacturer</i>
--------	--------------------------------------
