



# Cleartalk ASP-10D-2

Conference Speakerphone

### HD conference voice

32K sound pickup and 48K playback highly vocal, the sound i

# The 3<sup>rd</sup> generation of Auctopus audio processing algorithm

360\* high coverage, long pickup Upgrade full duplex technology

# Two cascade omnidirectional microphones

Two omnidirectional microphones can pick up and play at the same

## Perfect full-duplex

Two-way communication is more natural and smooth 5m w

# Portable MIC and speaker

No driver required,plug and play; New appearance design,mor suitable for various conference scenes

### Cleartalk HD Daisy Chain

#### Architecture

- Tabletop console contains audio processing functions ,USB function, indicator and touch key function
- USB cable
- · USB extend line

#### Dimension

· 217\*206\*45mm

#### Net Weight

· 667g (single speakerphone)

#### Color

· Business Black

#### Interface

· USB 2.0 ( compatible with USB 3.0 )

#### Microphone

- · Omnidirectional microphone
- · Voice bandwidth:100-16KHz
- Sensitivity: -38 dB

94dB SPL@1KHz

·SNR: 65dB

94dB SPL@1KHz . A-weight

#### Speaker

- ·2-inch anti-magnetic speakers
- ·4Ω5W
- ·100-24KHz

#### Power

- ·USB supply(DC 5V / 500mA)
- ·Built-in lithium battery

#### Audio

- ·384ms echo cancellation ·Dynamic noise reduction
- ·Full duplex
- ·360 degree pick-up range ·DSP audio processing

#### Computer system

- ·Windows 8 / Windows 7 / Windows 10/Windows XP.etc
- MAC 10.7 and above

#### Function

- support common computer softwares such as:
  - -Microsoft Teams
  - -Zoom -etc
- ·microphone mute
- ·loudspeaker mute
- volume up/down
- illuicatoi

#### **Environmental requirements**

Temperature: 5° -40° Humidity: 20 -85% (no condensation)

Noise level: <48db

Storage temperature: -10° -40°
Reverberation time: <0.5 seconds

#### Key

·microphone mute key ·loudspeaker mute key ·volume up/down keys

#### LED circle indicator

Green light always on: working normally

Red light is always on:

the microphone is muted

A row of green lights at the bottom: the speaker is muted Red light flashes 3 times at the bottom: Connecting to charge Green lights flashing at four

corners: normal standby
Red lights flashing at four corners:
low power indication

The green light at the bottom will flash 3 times every 5 minutes while charging

Long press the switch button at the bottom of the device for 3 seconds to switch on and off normally.

In standby mode, the device will automatically shut down after 20 minutes

#### Product execution standard

·YD/T 993-1998

·GB/T 9254-2008

-GB 4843.1-2011

